arXiv:1204.2922v1 [cs.IT] 13 Apr 2012

Secret Key Agreement Using Correlated Sources over the Generalized Multiple Access Channel

Somayeh Salimi, Mikael Skoglund
School of Electrical Engineering and ACCESS Linnaeus Center
KTH Royal Institute of Technology, Stockholm, Sweden
{somayen,skoglund}@ee.kth.se

***Abstract*—A secret key agreement setup between three users is considered in which each of the users 1 and 2 intends to share a secret key with user 3 and users 1 and 2 are eavesdroppers with respect to each other. The three users observe i.i.d. outputs of correlated sources and there is a generalized discrete memoryless multiple access channel (GDMMAC) from users 1 and 2 to user 3 for communication between the users. The secret key agreement is established using the correlated sources and the GDMMAC. In this setup, inner and outer bounds of the secret key capacity region are investigated. Moreover, for a special case where the channel inputs and outputs and the sources form Markov chains in some order, the secret key capacity region is derived. Also a Gaussian case is considered in this setup.**

I. INTRODUCTION

Secret key sharing between two legitimate users in the presence of an eavesdropper was considered in [1] and [2] in the source and the channel model. In the source model, all the three users could observe i.i.d. outputs of correlated sources and there was a noiseless public channel with unlimited capacity for communication between the two legitimate users, through which all communications could be intercepted by the eavesdropper. In [1], secret key capacity is characterized in the source model when the noiseless public channel is one-way. In [3], secret key sharing in a source model with public channel of limited capacity is investigated in which there is a helper with access to source observations correlated with the others observations. In [4], the same problem of sharing a secret key is investigated in the source model where instead of the public channel, there is a noisy broadcast channel from the transmitter to the receiver and the eavesdropper. In [5], secret key sharing was considered in a framework where two users intended to share secret keys with a base station and the two users were eavesdroppers of each other's key. In [5], all the three users can observe i.i.d. outputs of correlated sources and there is a noiseless public channel with unlimited capacity from users 1 and 2 to user 3.

Motivated by the above works, we consider secret key sharing in a framework similar to [5] but in more conformity with real communication scenarios since the realization of public channel with unlimited capacity is not compatible with the noisy nature of wireless networks. Hence, instead of public channels with unlimited capacity, we consider noisy channels for communication between the users. Each of the users 1 and 2, as network users, intends to share a secret key with user 3, as a base station, and users 1 and 2 are the eavesdroppers with respect to each other. The three users have access to correlated sources and there is a generalized discrete memoryless multiple access channel (GDMMAC) to transmit the required information from users 1 and 2 to user 3. Users 1 and 2 govern the channel inputs of the GDMMAC and each of the three users receives his corresponding output from the channel. Each of the users 1 and 2 generates a secret key from his observations and sends the required information via the GDMMAC to user 3. Users 1 and 2 use the channel outputs to eavesdrop each other's key. For this setup, we derive an inner bound of the secret key capacity region in which a combination of wiretap codebook and secret key generation codebook along with Wyner-Ziv codebook is used. Furthermore, an explicit outer bound of the secret key capacity region is given and for a special case, the secret key capacity region is derived. Also, the problem is discussed in a Gaussian case.

The rest of the paper is organized as follows: in Section II, the proposed model is described. In Section III, our main results are given. A special case is investigated in Section IV. A Gaussian example is discussed in Section V. Conclusion and suggestions for future works are given in Section VI. Proofs of the theorems are presented in Appendices. Throughout the paper, a random variable is denoted with an upper case letter (e.g X) and its realization is denoted with the corresponding lower case letter (e.g., x). We use X_i^N to indicate vector $(X_{i,1}, X_{i,2}, ..., X_{i,N})$, and $X_{i,j}^k$ to indicate vector $(X_{i,j}, X_{i,j+1}, ..., X_{i,k})$, where i denotes the index of the corresponding user.

II. PRELIMINARIES

Users 1, 2 and 3 observe correlated discrete memoryless sources S_1, S_2 and S_3, respectively, with joint distribution P_{S_1,S_2,S_3} in an i.i.d. manner. Furthermore, there is a GDMMAC with probability distribution $P_{Y_1,Y_2,Y_3|X_1,X_2}$, independent of the sources, where users 1 and 2 govern the inputs X_1 and X_2, and then, outputs Y_1, Y_2 and Y_3 are seen by users 1, 2 and 3, respectively. Each of users 1 and 2 intends to share a secret keys with user 3 where user 1 is the eavesdropper of user 2's secret key and vice versa.

For the secret key agreement, users 1 and 2 generate secret keys K_1 and K_2 as stochastic functions of the information available at them, i.e., S_1^N and S_2^N, respectively. For $i = 1, 2, ..., N$, the i-th channel inputs $X_{1,i}$ and $X_{2,i}$ are determined as stochastic mappings $X_{1,i} = f_{1,i}(S_1^N)$ and

$X_{2,i}=f_{2,i}(S_2^N)$ by users 1 and 2, respectively. These inputs are sent over the GDMMAC and then, channel outputs $Y_{1,i}, Y_{2,i}$ and $Y_{3,i}$ are observed by users 1, 2 and 3, respectively. User 3 computes estimates of keys K_1 and K_2 as:

$$(\hat{K}_1, \hat{K}_2) = g(Y_3^N, S_3^N) \tag{1}$$

where g is a deterministic function. Users 1 and 2 use the channel outputs Y_1^N and Y_2^N to eavesdrop on each other's key, respectively. For simplicity, we assume that the number of source observations is the same as the channel uses. When these are not the same, the results can be deduced by considering a normalization coefficient. All the keys and random variables take values from some finite sets. Now, we state the conditions that should be met in the described secret key sharing framework as shown in Fig.1.

Definition 1: In the secret key agreement strategy of the proposed model, the rate pair (R_1, R_2) is an achievable key rate pair if for every $\varepsilon > 0$ and sufficiently large N, we have:

$$\Pr\{(K_1, K_2) \neq (\hat{K}_1, \hat{K}_2)\} < \varepsilon \tag{2}$$

$$\tfrac{1}{N} I(K_1; S_2^N, X_2^N, Y_2^N) < \varepsilon \tag{3}$$

$$\tfrac{1}{N} I(K_2; S_1^N, X_1^N, Y_1^N) < \varepsilon \tag{4}$$

$$\tfrac{1}{N} H(K_1) > R_1 - \varepsilon \text{ and } \tfrac{1}{N} H(K_2) > R_2 - \varepsilon \tag{5}$$

Equation (2) means that user 3 correctly estimates the secret keys and equations (3) and (4) mean that users 1 and 2 effectively have no information about each other's secret keys.

Definition 2: The region containing all achievable secret key rate pairs (R_1, R_2) is the secret key capacity region.

III. MAIN RESULTS

Now, we state the main result of the paper.

Theorem 1: In the described model, all rate pairs in the closure of the convex hall of the set of all key rate pairs (R_1, R_2) that satisfy the following region are achievable:

$$\begin{cases} R_1 > 0, R_2 > 0 \\ R_1 \leq [I(U_1; S_3|U_2) - I(U_1; S_2|U_2)]^+ + [I(V_1; Y_3|V_2) - I(V_1; Y_2|V_2, X_2)]^+, \\ R_2 \leq [I(U_2; S_3|U_1) - I(U_2; S_1|U_1)]^+ + [I(V_2; Y_3|V_1) - I(V_2; Y_1|V_1, X_1)]^+, \\ R_1 + R_2 \leq [I(U_1, U_2; S_3) - I(U_1; S_2|U_2) - I(U_2; S_1|U_1) - I(U_1; U_2)]^+ \\ + [I(V_1, V_2; Y_3) - I(V_1; Y_2|V_2, X_2) - I(V_2; Y_1|V_1, X_1)]^+ \end{cases}$$

subject to the constraints:

$$I(U_1; S_1|U_2, S_3) \leq I(V_1; Y_3|V_2), I(U_2; S_2|U_1, S_3) \leq I(V_2; Y_3|V_1),$$
$$I(U_1, U_2; S_1, S_2|S_3) \leq I(V_1, V_2; Y_3),$$

for random variables taking values in sufficiently large finite sets according to the distributions:

$$p_1(u_1, u_2, s_1, s_2, s_3) = p(u_1|s_1)p(u_2|s_2)p(s_1, s_2, s_3),$$
$$p_1(v_1, v_2, x_1, x_2, y_1, y_2, y_3) = p(v_1)p(v_2)p(x_1|v_1)p(x_2|v_2)p(y_1, y_2, y_3|x_1, x_2).$$

The proof of Theorem 1 is given in Appendix I. Here, the sketch of the proof is given. To derive this inner bound, a part of the keys between the users is generated by using the source common randomness and the other part is generated by exploiting the channel common randomness. For this purpose, we impose the separation strategy as in [4] to the GDMMAC. At the first part of secret key sharing, users 1 and 2 generate secret keys using source observations. To share these keys with user 3, some information should be sent by users 1 and 2 via the GDMMAC according to Wyner-Ziv codebook for multiple sources as in [7] and this information should satisfy the constraints of Theorem 1. The information sent by each user is independent of his secret key. On the other hand, the GDMMAC is noisy and not all of the information sent by user 1 can be decoded by user 2 and vice versa. Hence, part of the information sent via the GDMMAC can be itself used for secret key generation exploiting the channel common randomness. The latter rates are achievable if they belong to the secrecy rate region of the GDMMAC in [6].



Fig. 1: Secret key sharing using correlated sources over GDMMAC

Proposition 1: The following region is an explicit outer bound of the secret key capacity region in the described setup:

$$0 \leq R_1 \leq I(X_1; Y_3|X_2, Y_2) + I(S_1; S_3|S_2),$$
$$0 \leq R_2 \leq I(X_2; Y_3|X_1, Y_1) + I(S_2; S_3|S_1),$$
$$0 \leq R_1 + R_2 \leq I(X_1, X_2; Y_3) + I(S_1, S_2; S_3).$$

The proof of Proposition 1 is given in Appendix II.

It should be noted that the separation strategy used in achievability may not be optimal in general and hence, we could not yet derive the secret key capacity region. In the next section, we investigate a special case where the rate region in Theorem 1 can achieve the capacity region.

IV. SPECIAL CASE

In this section, we consider a special case of the general problem discussed in the previous sections. This special case arises when the channel inputs and outputs and the sources form Markov chains as:

$$(X_1, X_2) - Y_1 - Y_3, \qquad (X_1, X_2) - Y_2 - Y_3, \qquad S_1 - S_3 - S_2.$$

Also, we constrain a special condition to the channel such that each of the channel inputs can be specified with access to the receiver's channel output and the other transmitter's input or in other words:

$$H(X_1|X_2, Y_3) = 0, \qquad H(X_2|X_1, Y_3) = 0.$$

In this case, the GDMMAC cannot itself provide secrecy; due to the Markov chains between the inputs and outputs, however, it can be used by users 1 and 2 to transmit the required information of the source common randomness. The secret key capacity region is given in the following theorem.

Theorem 2: In the mentioned special case of the described setup, the secret key capacity region is the set of all rate pairs (R_1, R_2) that satisfy:

$$R_1 \leq I(U_1; S_3|S_2), \qquad R_2 \leq I(U_2; S_3|S_1),$$

subject to the constraints:

$$I(U_1; S_1|S_3) \leq I(X_1; Y_3|X_2), I(U_2; S_2|S_3) \leq I(X_2; Y_3|X_1),$$
$$I(U_1; S_1|S_3) + I(U_2; S_2|S_3) \leq I(X_1, X_2; Y_3),$$

for random variables taking values in sufficiently large finite sets according to the distributions:

$$p(u_1, u_2, s_1, s_2, s_3) = p(u_1|s_1)p(u_2|s_2)p(s_1, s_2, s_3),$$
$$p_1(x_1, x_2, y_1, y_2, y_3) = p(x_1)p(x_2)p(y_1, y_2, y_3|x_1, x_2).$$

The achievability can be deduced from Theorem 1 by substituting $V_1 = X_1, V_2 = X_2$ and employing the Markov chains. The outer bound is proved in Appendix III. In this example, the GDMMAC is used just to transmit the required source common randomness information and hence, the problem can be treated as a pure source model with rate limited public channels. When the channel rates satisfy:

$$H(S_1|S_3) \leq I(X_1; Y_3|X_2), H(S_2|S_3) \leq I(X_2; Y_3|X_1),$$
$$H(S_1, S_2|S_3) \leq I(X_1, X_2; Y_3),$$

the case is similar to the special case of the forward source model of [5] where the secret key capacity is the union of all rate pairs that satisfy:

$$R_1 \leq I(S_1; S_3 |S_2) \ , \qquad R_2 \leq I(S_2; S_3 |S_1) \ .$$

V. A GAUSSIAN EXAMPLE

As a scalar Gaussian example, we consider the case where the source observations at the users are according to Markov chain $S_1 - S_3 - S_2$. Then, without loss of generality, we can model them as $S_1 = S_3 + E_{s,1}, S_2 = S_3 + E_{s,2}$ where $S_3, E_{s,1}$ and $E_{s,2}$ are independent zero mean Gaussian variables with variances $P_3, N_{s,1}$ and $N_{s,2}$, respectively. The GDMMAC is described by:

$$Y_3 = X_1 + X_2 + E_{c,3}, Y_2 = X_1 + X_2 + E_{c,2}, Y_1 = X_1 + X_2 + E_{c,1},$$

in which $E_{c,i} \sim \mathcal{N}(0, N_{c,i})$ for $i = 1, 2, 3$ with the input power constraints P_1 and P_2 at users 1 and 2, respectively. By the standard arguments as the discrete channel arguments, the results can be extended to Gaussian case. We consider:

$$V_1 = X_1, V_2 = X_2, S_1 = U_1 + D_1, S_2 = U_2 + D_2$$

in Theorem 1 where $U_i \sim \mathcal{N}(0, P_{U_i}), D_i \sim \mathcal{N}(0, P_3 + N_{s,i} - P_{U_i})$ and U_i is independent of D_i for $i = 1, 2$.

By substituting the random variables as above in Theorem 1, the following proposition for secret key rate region can be deduced for which the proof is relinquished due to space limitation.

Proposition 2: (R_1, R_2) is an achievable key rate pair if is satisfies the equations at the top of the next page.

For the values $P_1 = P_2 = P_3 = 1, N_{s,1} = N_{s,2} = N_{c,3} = 0.5$, the rate region is shown in Fig. 2 where $N_{c,1} = N_{c,2}$ and they vary from 0.5 to 0.9. When $N_{c,1} = N_{c,2} = 0.5$, no secret key can be generated through GDMMAC and the second terms of the secret key rates bound in Proposition 2 will be zero. In this case, the region is the secret key rate region of a pure source model with rate limited public channels. When these noises increase, the key rate region enlarges however the sum rate boundary remains fixed since the sum rate term related to channel common randomness is zero until these noises amount to about $N_{c,1} = N_{c,2} = 0.75$. At this point, the term related to the channel common randomness in the sum rate bound would be positive and hence, the sum rate bound increases. For $N_{c,1} = N_{c,2} = 0.8$, the rate region is rectangular since each user's rate bound in proposition 2 will exceed the total sum rate bound. For $N_{c,1} = N_{c,2} = 0.9$, this region becomes pentagonal as the sum rate due to channel common randomness is increased such that the total sum rate bound dominates each user's rate bound.



Fig. 2: Secret key rate region for different values of N_{c1} and N_{c2}

VI. CONCLUSION

The problem of secret key sharing in a combined framework with both source and the channel common randomness was studied. For this problem, the inner bound and the explicit outer bound of the secret key capacity region were derived. The separation strategy used to achieve the inner bound was not optimal in general, however, for the especial case where the channel inputs and outputs and the sources form Markov chains in some order, the secret key capacity region was derived. It was shown that this case can be simulated as the source model of key agreement with public channels of limited capacity. As future work, the joint source channel coding can be investigated instead of the separation strategy. In addition, in a more practical scenario, some types of dependency between the source and the channel can be supposed.

APPENDIX I

Proof of Theorem 1

We fix the distribution to be the same as in Theorem 1. Users 1 and 2 independently and randomly generate typical sequences u_1^N and u_2^N, respectively, each with probability:

$$p(u_1^N) = \prod_{i=1}^{N} p(u_{1,i}), p(u_2^N) = \prod_{i=1}^{N} p(u_{2,i}).$$

The number of the sequences u_1^N and u_2^N are $2^{N(I(U_1;S_1)+\varepsilon')}$, and $2^{N(I(U_2;S_2)+\varepsilon')}$, respectively, in which $\varepsilon' > 0$ can be chosen arbitrarily small. Using two-layered random binning, they are labeled as:

$$u_1^N(k_{1S}, k'_{1S}, k''_{1S}),$$
$$k_{1S} \in \{1, ..., 2^{Nr_{1S})}\}, k'_{1S} \in \{1, ..., 2^{Nr'_{1S}}\}, k''_{1S} \in \{1, ..., 2^{Nr''_{1S}}\}$$
$$u_2^N(k_{2S}, k'_{2S}, k''_{2S}),$$
$$k_{2S} \in \{1, ..., 2^{Nr_{2S})}\}, k'_{2S} \in \{1, ..., 2^{Nr'_{2S}}\}, k''_{2S} \in \{1, ..., 2^{Nr''_{2S}}\}$$

where:

$$r_{1S} + r'_{1S} = I(U_1; S_1) - I(U_1; S_2) + 2\varepsilon', r''_{1S} = I(U_1; S_2) - \varepsilon', \qquad (6)$$
$$r_{2S} + r'_{2S} = I(U_2; S_2) - I(U_2; S_1) + 2\varepsilon', r''_{2S} = I(U_2; S_1) - \varepsilon', \qquad (7)$$

It is obvious that $r_{1S} + r'_{1S} + r''_{1S} = I(U_1; S_1) + \varepsilon'$ and so, each sequence u_1^N can be determined if the indices $(k_{1S}, k'_{1S}, k''_{1S})$ are known. The same is true for u_2^N.

$$
\begin{aligned}
&R_1 > 0, R_2 > 0,\\
&R_1 \le \tfrac{1}{2}\log(1+\tfrac{P_{U_1}P_3N_{s,2}}{((P_3+N_{s,1})^2-P_{U_1}P_3)(P_3+N_{s,2})}) + \tfrac{1}{2}[\log(1+\tfrac{P_1}{N_{c,3}}) - \log(1+\tfrac{P_1}{N_{c,2}})]^+,\\
&R_2 \le \tfrac{1}{2}\log(1+\tfrac{P_{U_2}P_3N_{s,1}}{((P_3+N_{s,2})^2-P_{U_2}P_3)(P_3+N_{s,1})}) + \tfrac{1}{2}[\log(1+\tfrac{P_2}{N_{c,3)}}) - \log(1+\tfrac{P_2}{N_{c,1}})]^+,\\
&R_1 + R_2 \le \tfrac{1}{2}\log[(1+\tfrac{P_{U_1}P_3N_{s,2}}{((P_3+N_{s,1})^2-P_{U_1}P_3)(P_3+N_{s,2})})(1+\tfrac{P_{U_2}P_3N_{s,1}}{((P_3+N_{s,2})^2-P_{U_2}P_3)(P_3+N_{s,1})})]\\
&+\tfrac{1}{2}[\log(1+\tfrac{P_1+P_2}{N_{c,3)}}) - \log(1+\tfrac{P_1}{N_{c,2}}) - \log(1+\tfrac{P_2}{N_{c,1}})]^+
\end{aligned}
$$

due to the constraints:

$$
\begin{aligned}
&P_{U_1} \le \tfrac{P_1(P_3+N_{s,1})^2}{N_{s,1}N_{c,3}+P_1(P_3+N_{s,1})}, \qquad P_{U_2} \le \tfrac{P_2(P_3+N_{s,2})^2}{N_{s,2}N_{c,3}+P_2(P_3+N_{s,2})},\\
&(A_1 - P_{U_1})(A_2 - P_{U_2}) \ge A_1A_2 - \tfrac{(P_1+P_2)(P_3+N_{s,1})^2(P_3+N_{s,2})^2}{A},\\
&A = N_{s,1}N_{s,2}N_{c,3} + P_3N_{c,3}(N_{s,1}+N_{s,2}) + (P_1+P_2)(P_3+N_{s,1})(P_3+N_{s,2}),\\
&A_1 = \tfrac{(P_3+N_{s,1})^2(N_{s,2}N_{c,3}+(P_1+P_2)(P_3+N_{s,2}))}{A}, A_2 = \tfrac{(P_3+N_{s,2})^2(N_{s,1}N_{c,3}+(P_1+P_2)(P_3+N_{s,1}))}{A}.
\end{aligned}
$$

In addition to the secret key codebooks, the wiretap channel codebooks are generated. Users 1 and 2 generate independent sequences v_1^N and v_2^N, respectively, each with probability:

$$p(v_1^N) = \prod_{i=1}^{N} p(v_{1,i}), p(v_2^N) = \prod_{i=1}^{N} p(v_{2,i})$$

The number of sequences v_1^N and v_2^N is $2^{N(r_{1C}+r'_{1C})}$ and $2^{N(r_{2C}+r'_{2C})}$, respectively, which are labeled as:

$$v_1^N(k_{1C}, k'_{1C}), k_{1C} \in \{1, ..., 2^{Nr_{1C}}\}, k'_{1C} \in \{1, ..., 2^{Nr'_{1C}}\}$$
$$v_2^N(k_{2C}, k'_{2C}), k_{2C} \in \{1, ..., 2^{Nr_{2C}}\}, k'_{2C} \in \{1, ..., 2^{Nr'_{2C}}\}$$

where:

$$r'_{1C} = I(V_1; X_2, Y_2|V_2) - \varepsilon'', r'_{2C} = I(V_2; X_1, Y_1|V_1) - \varepsilon'' \quad (8)$$

Two functions f_1 and f_2 are defined as:

$$
\begin{aligned}
&f_1 : \mathcal{V}_1 \to \mathcal{K}'_{1S}, && f_2 : \mathcal{V}_2 \to \mathcal{K}'_{2S},\\
&\mathcal{K}'_{1S} = \{1, ..., 2^{Nr'_{1S}}\}, && \mathcal{K}'_{2S} = \{1, ..., 2^{Nr'_{2S}}\},
\end{aligned}
$$

where $\mathcal{V}_1$ and $\mathcal{V}_2$ are the set of $2^{N(r_{1C}+r'_{1C})}$ and $2^{N(r_{2C}+r'_{2C})}$ codewords v_1^N and v_2^N, respectively. Mapping f_1 is a random partitioning of codewords v_1^N into $2^{Nr'_{1S}}$ equal-sized parts. Elements of part i are labeled as $(\mathcal{V}_1)_i$. Mapping f_2 is similarly defined. In the definition of f_1, we assume that $r_{1C}+r'_{1C} \ge r'_{1S}$ and as we would see in the decoding step, this can be deduced from the constraint of Theorem 1. The same is true for f_2.

For encoding, when typical sequences s_1^N and s_2^N are observed at users 1 and 2, respectively, sequences u_1^N and u_2^N are chosen at the corresponding users such that (s_1^N, u_1^N) and (s_2^N, u_2^N) are $\varepsilon'-$jointly typical. It can be seen that these sequences are unique with high probability for arbitrarily small ε'. For the sequences $u_1^N(k_{1S}, k'_{1S}, k''_{1S})$ and $u_2^N(k_{2S}, k'_{2S}, k''_{2S})$, the indices k_{1S} and k_{2S} are chosen by users 1 and 2, respectively, to share with user 3 as the secret keys due to the source observations. For this purpose, the indices k'_{1S} and k'_{2S} are the required information to be sent by users 1 and 2 to user 3. User 1 encodes k'_{1S} in such a way that he returns v_1^N randomly chosen from $(\mathcal{V}_1)_{k'_{2S}}$ using the mapping f_1. User 2 acts in a same way using mapping f_2 and returns v_2^N. For the selected $v_1^N(k_{1C}, k'_{1C})$ and $v_2^N(k_{2C}, k'_{2C})$, user 1 and 2, respectively, consider k_{1C} and k_{2C} to share with user 3 as the secret keys due to the channel common randomness. Then, the channel inputs x_1^N and x_2^N are sent over GDMMAC according to the distributions $p(x_1|v_1)$ and $p(x_2|v_2)$.

For decoding, user 3, first, chooses the sequences v_1^N and v_2^N which are ε_1-jointly typical with the received y_3^N where $\varepsilon_1 = \frac{\varepsilon}{8}$. User 3 decodes key pair (k_{1C}, k_{2C}) if $(v_1^N(k_{1C}, k'_{1C}), v_2^N(k_{2C}, k'_{2C}), y_3^N) \in A_{\varepsilon_1}^{(N)}(P_{V_1,V_2,Y_3})$, when such $(v_1^N(k_{1C}, k'_{1C}), v_2^N(k_{2C}, k'_{2C}))$ exists and is unique. Otherwise, it declares error. It can be shown that the decoding error probability of this step is bounded as:

$$P_{e1}^{(N)} \le \varepsilon_1 + 2^{N(r_{1C}+r'_{1C}+r_{2C}+r'_{2C}-(I(V_1,V_2;Y_3)-4\varepsilon_1))} + 2^{N(r_{1C}+r'_{1C}-(I(V_1;Y_3|V_2)-3\varepsilon_1))} + 2^{N(r_{2C}+r'_{2C}-(I(V_2;Y_3|V_1)-3\varepsilon_1))}.$$

If we set:

$$r_{1C} < I(V_1;Y_3|V_2) - I(V_1;X_2,Y_2|V_2), r_{2C} < I(V_2;Y_3|V_1) - I(V_2;X_1,Y_1|V_1),$$
$$r_{1C} + r_{2C} < I(V_1, V_2; Y_3) - I(V_1; X_2, Y_2|V_2) - I(V_2; X_1, Y_1|V_1),$$

then by substituting r'_{1C} and r'_{2C} from (8), we have:

$$P_{e1}^{(N)} \le \varepsilon_1 + 2^{N(-2\varepsilon''+4\varepsilon_1)} + 2^{N(-\varepsilon''+3\varepsilon_1)} + 2^{N(-\varepsilon''+3\varepsilon_1)}.$$

By setting $\varepsilon'' > 3\varepsilon_1 = \frac{3\varepsilon}{8}$, for example $\varepsilon'' = 4\varepsilon_1 = \frac{\varepsilon}{2}$, we choose N so large that $2^{N(-\varepsilon''+3\varepsilon_1)} \le \varepsilon_1$, and then $P_{e1}^{(N)} \le 4\varepsilon_1 = \frac{\varepsilon}{2}$. After correct decoding (k_{1C}, k'_{1C}) and (k_{2C}, k'_{2C}), user 3 considers k_{1C} and k_{2C} to share with users 1 and 2, respectively, as the secret keys due to the channel common randomness. Then, using functions f_1 and f_2, user 3 finds the mappings $(\mathcal{V}_1)_i$ of the codeword v_1^N and $(\mathcal{V}_2)_j$ of the codeword v_2^N and sets $k'_{1S} = i, k'_{2S} = j$. Now, user 3 decodes sequences $u_1^N(k_{1S}, k'_{1S}, k''_{1S})$ and $u_2^N(k_{2S}, k'_{2S}, k''_{2S})$ such that:

$$(u_1^N(k_{1S}, k'_{1S} = i, k''_{1S}), u_2^N(k_{2S}, k'_{2S} = j, k''_{2S}), s_3^N) \in A_{\varepsilon_2}^{(N)}(P_{U_1,U_2,S_3}),$$

when such $(u_1^N(k_{1S}, k'_{1S}, k''_{1S}), u_2^N(k_{2S}, k'_{2S}, k''_{2S}))$ exists and is unique. Otherwise, it declares error. For $\varepsilon_2 = \frac{\varepsilon}{16}$, according to Wyner-Ziv problem for multiple sources in [7], the decoding error probability of this step is bounded as:

$$P_{e2}^{(N)} \le \varepsilon_2 + 2^{N(14\varepsilon_2+I(U_1,U_2;S_1,S_2|S_3)-(r'_{1S}+r'_{2S}))} + 2^{N(7\varepsilon_2+I(U_1;S_1|U_2,S_3)-r'_{1S})} + 2^{N(7\varepsilon_2+I(U_2;S_2|U_1,S_3)-r'_{2S})}.$$

If we set:
$r_{1S} < I(U_1;S_3|U_2) - I(U_1;S_2|U_2),$
$r_{2S} < I(U_2;S_3|U_1) - I(U_2;S_1|U_1),$
$r_{1S}+r_{2S} < I(U_1,U_2;S_3) - I(U_1;S_2|U_2) - I(U_2;S_1|U_1) - I(U_1;U_2),$

then by substituting r'_{1S} and r'_{2S} from (6) and (7), we have:

$$P_{e2}^{(N)} \leq \varepsilon_2 + 2^{N(14\varepsilon_2 - 4\varepsilon')} + 2^{N(7\varepsilon_2 - 2\varepsilon')} + 2^{N(7\varepsilon_2 - 2\varepsilon')}.$$

By setting $\varepsilon' > \frac{7}{2}\varepsilon_2$, for example $\varepsilon' = 4\varepsilon_2 = \frac{\varepsilon}{4}$, we choose N so large that $2^{N(14\varepsilon_2 - 4\varepsilon')} \leq \varepsilon_2$, and then $P_{e2}^{(N)} \leq 4\varepsilon_2 = \frac{\varepsilon}{4}$. After this step of decoding, user 3 considers k_{1S} and k_{2S} to share with users 1 and 2, respectively, as the secret keys due to the source observations.

By the above arguments, the total decoding error probability is bounded as $P_e^{(N)} \leq P_{e1}^{(N)} + P_{e2}^{(N)} \leq \frac{\varepsilon}{2} + \frac{\varepsilon}{4} < \varepsilon$.

For correct decoding in the first step, according to $P_{e1}^{(N)}$ equation, it is necessary that:

$$r_{1C}+r'_{1C} < I(V_1;Y_3|V_2)\ , r_{2C}+r'_{2C} < I(V_2;Y_3|V_1)$$
$$r_{1C}+r'_{1C} + r_{2C}+r'_{2C} < I(V_1,V_2;Y_3)$$

and hence, considering the rate constraints in Theorem 1, the functions f_1 and f_2 can be defined.

Now, we should check the security conditions of definition 1 and show that the indices (k_{1S}, k_{1C}) can be shared as secret keys between user 1 and user 3 and (k_{2S}, k_{2C}) can be shared as secret keys between user 2 and user 3. We give the proof of (3) and by symmetry, (4) can be deduced. We have:

$$I(K_{1S},K_{1C};S_2^N,X_2^N,Y_2^N) = \underbrace{I(K_{1S};S_2^N,X_2^N,Y_2^N|K_{1C})}_{A} + \underbrace{I(K_{1C};S_2^N,X_2^N,Y_2^N)}_{B}$$

Now, we analyze each term separately. We consider $\varepsilon_3 = \varepsilon_4 = \varepsilon_5 = \varepsilon_6 = \frac{\varepsilon}{8}$. Some Markov chains useful in the security analysis are given in continue. These Markov chains arise from the coding scheme.

$$(U_1^N,U_2^N) - (K'_{1S},K'_{2S}) - (V_1^N,V_2^N) - (X_1^N,X_2^N) - (Y_1^N,Y_2^N,Y_3^N) \quad (9)$$
$$U_1^N - S_1^N - S_2^N - U_2^N \quad (10)$$
$$V_1^N - V_2^N - K'_{2S} - U_2^N - S_2^N \quad (11)$$

For term A, we have:

$$\begin{aligned}
&I(K_{1S};S_2^N,X_2^N,Y_2^N|K_{1C}) \leq I(K_{1S};S_2^N,X_2^N,Y_2^N,K_{1C})\\
&\leq I(K_{1S};S_2^N,X_2^N,Y_2^N,K_{1C},K'_{1S},K'_{2S})\\
&\overset{(a)}{=} I(K_{1S};S_2^N,K'_{1S},K'_{2S})\\
&\overset{(b)}{=} I(K_{1S};S_2^N,K'_{1S}) = H(K_{1S}) - H(K_{1S}|S_2^N,K'_{1S})\\
&= H(K_{1S}) - H(K_{1S},U_1^N|S_2^N,K'_{1S}) + H(U_1^N|S_2^N,K'_{1S},K_{1S})\\
&\overset{(c)}{\leq} H(K_{1S}) - H(K_{1S},U_1^N|S_2^N,K'_{1S}) + N\varepsilon_3\\
&\leq H(K_{1S}) - H(U_1^N|S_2^N,K'_{1S}) + N\varepsilon_3\\
&\leq H(K_{1S}) - H(U_1^N,K'_{1S}|S_2^N) + H(K'_{1S}|S_2^N) + N\varepsilon_3\\
&\overset{(d)}{=} H(K_{1S}) - H(U_1^N|S_2^N) + H(K'_{1S}|S_2^N) + N\varepsilon_3\\
&\leq H(K_{1S}) - H(U_1^N|S_2^N) + H(K'_{1S}) + N\varepsilon_3\\
&= N(I(U_1;S_1) - I(U_1;S_2) + 2\varepsilon') - H(U_1^N|S_2^N) + N\varepsilon_3\\
&\overset{(e)}{\leq} N(I(U_1;S_1) - I(U_1;S_2) + 2\varepsilon') - NH(U_1|S_2) + N\varepsilon_4 + N\varepsilon_3\\
&\leq N\varepsilon_3 + 2N\varepsilon' + N\varepsilon_4 = N\tfrac{3\varepsilon}{4}.
\end{aligned}$$

In above equations, (a) and (b) follow from Markov chains (9) and (10), respectively. (c) can be deduced from the same approach as lemma 2 in [6] to show $H(U_1^N|S_2^N,M'_1,M_1) \leq N\varepsilon_3$. (d) follows from the fact that k'_{1S} is one of the indices of u_1^N. To prove (e), the same approach as lemma 3 in [6] is exploited to show $NI(U_1|S_2) \leq I(U_1^N|S_2^N) + N\varepsilon_4$.

For term B, we have:

$$\begin{aligned}
&I(K_{1C};S_2^N,X_2^N,Y_2^N) \leq I(K_{1C};S_2^N,X_2^N,Y_2^N,V_2^N)\\
&= H(K_{1C}) - H(K_{1C}|S_2^N,X_2^N,Y_2^N,V_2^N)\\
&= H(K_{1C}) - H(K_{1C},V_1^N|S_2^N,X_2^N,Y_2^N,V_2^N) +\\
&\quad H(V_1^N|K_{1C},S_2^N,X_2^N,Y_2^N,V_2^N)\\
&\overset{(a)}{\leq} H(K_{1C}) - H(K_{1C},V_1^N|S_2^N,X_2^N,Y_2^N,V_2^N) + N\varepsilon_5\\
&\overset{(b)}{=} H(K_{1C}) - H(V_1^N|S_2^N,X_2^N,Y_2^N,V_2^N) + N\varepsilon_5\\
&\overset{(c)}{=} H(K_{1C}) - H(V_1^N|X_2^N,Y_2^N,V_2^N) + N\varepsilon_5\\
&\overset{(d)}{\leq} H(K_{1C}) - NH(V_1|X_2,Y_2,V_2) + N\varepsilon_5 + N\varepsilon_6\\
&\overset{(e)}{\leq} N(I(V_1;Y_3|V_2) - I(V_1;X_2,Y_2|V_2)) - NH(V_1|X_2,Y_2,V_2) +\\
&\quad N\varepsilon_5 + N\varepsilon_6\\
&= -NH(V_1|Y_3,V_2) + N\varepsilon_5 + N\varepsilon_5\\
&\leq N\varepsilon_5 + N\varepsilon_6 = N\tfrac{\varepsilon}{4}
\end{aligned}$$

In the above equations, (a) can be deduced from the same approach as lemma 2 in [6] to show $H(V_1^N|K_{1C},X_2^N,Y_2^N,V_2^N) \leq N\varepsilon_5$. (b) follows from the fact that k_{1C} is one of the indices of v_1^N.(c) can be followed from Markov chain (11). The same approach as lemma 3 in [6] can be exploited to show $NH(V_1|X_2,Y_2,V_2) \leq H(V_1^N|X_2^N,Y_2^N,V_2^N) + N\varepsilon_6$. (e) is a direct consequence of reliable decoding at user 3.
Hence, the security condition (3) is satisfied as:

$$I(K_{1S},K_{1C};S_2^N,X_2^N,Y_2^N) \leq N(\frac{3\varepsilon}{4} + \frac{\varepsilon}{4}) = N\varepsilon.$$

To show that the total rate of user 1's key is sum of r_{1S} and r_{1C}, we should prove the independency of the keys of the two steps. When analyzing term A of the security condition, we show that $I(K_{1S};S_2^N,X_2^N,Y_2^N,K_{1C}) \leq N\frac{3\varepsilon}{4}$ and hence $I(K_{1S};K_{1C}) \leq N\varepsilon$, and this completes the proof of theorem 1.

APPENDIX II

Proof of the explicit outer bound in Lemma 1

First, users 1 and 2 generate secret keys K_1 and K_2, respectively, as stochastic functions $K_1 = f_1(S_1^N)$ and $K_2 = f_2(S_2^N)$. Then, they determine the channel inputs as stochastic functions $X_1^N = f_3(S_1^N)$ and $X_2^N = f_4(S_2^N)$ and send them via The GDMMAC. Consequently, Y_1^N, Y_2^N and Y_3^N are received by user 1, user 2 and user 3, respectively. User 3 should be able to reconstruct the secret keys and according to Fano's inequality for an arbitrary small $\varepsilon > 0$:

$$H(K_1,K_2|Y_3^N,S_3^N) \leq N(\frac{H(\varepsilon)}{N} + \varepsilon(\log|\mathcal{K}_1||\mathcal{K}_2| - 1)) \triangleq N\varepsilon_1,$$

where $\varepsilon_1 \to 0$ if $\varepsilon \to 0$. Also, the following security conditions should be satisfied as:

$$I(K_1;S_2^N,X_2^N,Y_2^N) < N\varepsilon, \quad I(K_2;S_1^N,X_1^N,Y_1^N) < N\varepsilon.$$

Now, we show that for the secret keys satisfying the reliability and security conditions described above, we can deduce the explicit outer bound of Lemma 1. We prove the outer bound on R_1 (symmetry can be used for R_2).

$$\begin{aligned}
&R_1 = \tfrac{1}{N}H(K_1) \overset{(a)}{\le} \tfrac{1}{N}H(K_1 \,|S_2^N, X_2^N, Y_2^N) + \varepsilon\\
&\overset{(b)}{\le} \tfrac{1}{N}H(K_1 \,|S_2^N, X_2^N, Y_2^N) - \tfrac{1}{N}H(K_1 \,|S_3^N, Y_3^N) + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}I(K_1; S_3^N, Y_3^N \,|S_2^N, X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}I(S_1^N, X_1^N; S_3^N, Y_3^N \,|S_2^N, X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&= \tfrac{1}{N}I(S_1^N, X_1^N; S_3^N|S_2^N, X_2^N, Y_2^N)+\\
&\quad \tfrac{1}{N}I(S_1^N, X_1^N; Y_3^N|S_3^N, S_2^N, X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&= \tfrac{1}{N}(H(S_3^N \,|S_2^N, X_2^N, Y_2^N) - H(S_3^N \,|S_1^N, X_1^N; S_2^N, X_2^N, Y_2^N))\\
&+\tfrac{1}{N}I(S_1^N, X_1^N; Y_3^N \,|S_3^N, S_2^N, X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}(H(S_3^N \,|S_2^N) - H(S_3^N \,|S_1^N, X_1^N, S_2^N, X_2^N, Y_2^N))\\
&+\tfrac{1}{N}I(S_1^N, X_1^N; Y_3^N \,|S_3^N, S_2^N, X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&\overset{(c)}{=} \tfrac{1}{N}(H(S_3^N \,|S_2^N) - H(S_3^N \,|S_1^N, S_2^N))\\
&+\tfrac{1}{N}I(S_1^N, X_1^N; Y_3^N \,|S_3^N, S_2^N, X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}(I(S_3^N; S_1^N \,|S_2^N)) + \tfrac{1}{N}(H(Y_3^N \,|X_2^N, Y_2^N)\\
&-H(Y_3^N \,|S_1^N, X_1^N, S_3^N, S_2^N, X_2^N, Y_2^N)) + \varepsilon_1 + \varepsilon\\
&\overset{(d)}{=} \tfrac{1}{N}I(S_3^N; S_1^N|S_2^N) + \tfrac{1}{N}(H(Y_3^N|X_2^N, Y_2^N)-\\
&\quad H(Y_3^N|X_1^N, X_2^N, Y_2^N)) + \varepsilon_1 + \varepsilon\\
&= \tfrac{1}{N}I(S_1^N; S_3^N \,|S_2^N) + \tfrac{1}{N}I(X_1^N; Y_3^N \,|X_2^N, Y_2^N) + \varepsilon_1 + \varepsilon\\
&\le I(S_1; S_3 \,|S_2) + I(X_1; Y_3 \,|X_2, Y_2) + \varepsilon_1 + \varepsilon
\end{aligned}$$

where (a) results from the security condition, (b) from Fano's inequality, (c) from the fact that given (S_1, S_2), S_3 is independent of (X_1, X_2, Y_2) and (d) from the fact that given (X_1, X_2), Y_3 is independent of (S_1, S_2, S_3).

The sum rate upper bound can be deduced from Fano's equality.

APPENDIX III

Proof of the converse in Theorem 2

To derive the outer bound in Theorem 2, for an arbitrary small $\varepsilon > 0$, we use Fano's inequality and security conditions as:

$$H(K_1, K_2|Y_3^N, S_3^N) \le N(\tfrac{H(\varepsilon)}{N} + \varepsilon(\log|\mathcal{K}_1||\mathcal{K}_2| - 1)) \triangleq N\varepsilon_1,$$
$$I(K_1; S_2^N, X_2^N, Y_2^N) < N\varepsilon,\ I(K_2; S_1^N, X_1^N, Y_1^N) < N\varepsilon,$$

where $\varepsilon_1 \to 0$ if $\varepsilon \to 0$. We prove the outer bound of R_1. The outer bound of R_2 can be deduced by symmetry.

$$\begin{aligned}
&R_1 = \tfrac{1}{N}H(K_1) \overset{(a)}{\le} \tfrac{1}{N}H(K_1 \,|S_2^N, X_2^N, Y_2^N) + \varepsilon\\
&\overset{(b)}{\le} \tfrac{1}{N}H(K_1 \,|S_2^N, X_2^N, Y_3^N) + \varepsilon\\
&\overset{(c)}{\le} \tfrac{1}{N}H(K_1 \,|S_2^N, X_2^N, Y_3^N) - \tfrac{1}{N}H(K_1 \,|S_3^N, Y_3^N) + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}H(K_1|S_2^N, X_2^N, Y_3^N) - \tfrac{1}{N}H(K_1|S_2^N, X_2^N, S_3^N, Y_3^N) + \varepsilon_1 + \varepsilon\\
&\overset{(d)}{=} \tfrac{1}{N}H(K_1|S_2^N, X_1^N, X_2^N, Y_3^N) - \tfrac{1}{N}H(K_1|S_2^N, X_1^N, X_2^N, S_3^N, Y_3^N) + \varepsilon_1 + \varepsilon\\
&\overset{(e)}{=} \tfrac{1}{N}H(K_1|S_2^N, X_1^N, X_2^N) - \tfrac{1}{N}H(K_1|S_2^N, X_1^N, X_2^N, S_3^N) + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}H(K_1 \,|S_2^N, X_1^N) - \tfrac{1}{N}H(K_1 \,|S_2^N, X_1^N, S_3^N) + \varepsilon_1 + \varepsilon\\
&= \tfrac{1}{N}I(K_1; S_3^N|S_2^N, X_1^N) + \varepsilon_1 + \varepsilon \le \tfrac{1}{N}I(K_1, X_1^N; S_3^N|S_2^N) + \varepsilon_1 + \varepsilon\\
&= \tfrac{1}{N}\textstyle\sum_{i=1}^N I(K_1, X_1^N; S_{3,i} \,|S_{3,i+1}^N, S_2^N) + \varepsilon_1 + \varepsilon\\
&\overset{(f)}{=} \tfrac{1}{N}\textstyle\sum_{i=1}^N I(K_1, X_1^N; S_{3,i} \,|S_{3,i+1}^N, S_{2,1}^i) + \varepsilon_1 + \varepsilon\\
&= \tfrac{1}{N}\textstyle\sum_{i=1}^N [H(S_{3,i}|S_{3,i+1}^N, S_{2,1}^i) - H(S_{3,i}|S_{3,i+1}^N, S_{2,1}^i, K_1, X_1^N)] + \varepsilon_1 + \varepsilon\\
&\le \tfrac{1}{N}\textstyle\sum_{i=1}^N [H(S_{3,i}|S_{2,i}) - H(S_{3,i}|S_{3,i+1}^N, S_{2,1}^i, S_{1,1}^{i-1}, K_1, X_1^N)] + \varepsilon_1 + \varepsilon\\
&\overset{(g)}{=} \textstyle\sum_{i=1}^N [H(S_{3,i}|S_{2,i}) - H(S_{3,i}|S_{3,i+1}^N, S_{2,i}, S_{1,1}^{i-1}, K_1, X_1^N)] + \varepsilon_1 + \varepsilon\\
&\overset{(h)}{=} \tfrac{1}{N}\textstyle\sum_{i=1}^N I(U_{1,i}; S_{3,i} \,|S_{2,i}) + \varepsilon_1 + \varepsilon \overset{(i)}{=} I(U_{1,Q}; S_{3,Q} \,|S_{2,Q}) + \varepsilon'
\end{aligned}$$

where (a) results from the security condition, (b) from the Markov chain $(X_1,X_2) - Y_2 - Y_3$, (c) from Fano's inequality, (d) from the fact that $H(X_1|X_2,Y_3) = 0$, (e) from the fact that given (X_1,X_2), Y_3 is independent of (S_1,S_2,S_3),(f) from the fact that given $S_{3,i+1}^N$,(K_1, X_1^N) is independent of $S_{2,i+1}^N$ which is the direct consequence of the Markov chain $S_1 - S_3 - S_2$, (g) from the Markov chain $S_{3,i} - (S_{3,i+1}^N, S_{2,i}, S_{1,1}^{i-1}, K_1, X_1^N) - S_{2,1}^{i-1}$ which arises because (K_1, X_1^N) is a function of S_1^N, (h) from the definition of the random variable $U_{1,i}$ as:

$$U_{1,i} = (S_{3,i+1}^N, S_{1,1}^{i-1}, K_1, X_1^N)$$

and (i) from the definition of the random variable Q which is uniformly distributed on $\{1,2,...,N\}$ and setting $\varepsilon' = \varepsilon_1 + \varepsilon$. With the same approaches as above, we have $R_2 \le I(U_{2,Q}; S_{3,Q}|S_{1,Q}) + \varepsilon'$ where $U_{2,i}$ is defined as $U_{2,i} = (S_{3,1}^{i-1}, S_{2,i+1}^N, K_2, X_2^N)$. It can be seen that the defined random variables satisfy the distribution of theorem 2.

To prove the rate constraints of Theorem 2, we have:

$$\begin{aligned}
&NI(X_1; Y_3 \,|X_2) \ge I(X_1^N; Y_3^N \,|X_2^N) \ge I(S_1^N; Y_3^N \,|X_2^N)\\
&\overset{(a)}{\ge} I(S_1^N; Y_3^N \,|X_2^N) + H(K_1 \,|S_3^N, Y_3^N, X_2^N) - N\varepsilon_1\\
&\ge I(S_1^N; Y_3^N|X_2^N) + H(K_1|S_3^N, Y_3^N, X_2^N) - H(K_1|S_1^N, Y_3^N, X_2^N) - N\varepsilon_1\\
&= I(S_1^N; Y_3^N, K_1 \,|X_2^N) - I(S_3^N; K_1 \,|Y_3^N, X_2^N) - N\varepsilon_1\\
&\ge I(S_1^N; Y_3^N, K_1 \,|X_2^N) - I(S_3^N; Y_3^N, K_1 \,|X_2^N) - N\varepsilon_1\\
&\overset{(b)}{=} I(S_1^N; Y_3^N, K_1, X_1^N \,|X_2^N) - I(S_3^N; Y_3^N, K_1, X_1^N \,|X_2^N) - N\varepsilon_1\\
&\overset{(c)}{=} I(S_1^N; K_1, X_1^N \,|X_2^N) - I(S_3^N; K_1, X_1^N \,|X_2^N) - N\varepsilon_1\\
&\overset{(d)}{=} H(K_1, X_1^N \,|S_3^N) - I(K_1, X_1^N \,|S_1^N) - N\varepsilon_1\\
&= I(S_1^N; K_1, X_1^N) - I(S_3^N; K_1, X_1^N) - N\varepsilon_1\\
&= I(K_1, X_1^N; S_1^N|S_3^N) - N\varepsilon_1 = \textstyle\sum_{i=1}^N I(K_1, X_1^N; S_{1,i}|S_3^N, S_{1,1}^{i-1}) - N\varepsilon_1\\
&= \textstyle\sum_{i=1}^N I(K_1, X_1^N; S_{1,i} \,|S_{3,i}^N, S_{1,1}^{i-1}) - N\varepsilon_1\\
&= \textstyle\sum_{i=1}^N [H(S_{1,i} \,|S_{3,i}) - H(S_{1,i} \,|S_{3,i}^N, S_{1,1}^{i-1}, K_1, X_1^N)] - N\varepsilon_1\\
&= \textstyle\sum_{i=1}^N I(K_1, X_1^N, S_{3,i+1}^N, S_{1,1}^{i-1}; S_{1,i} \,|S_{3,i}) - N\varepsilon_1\\
&= I(U_{1,Q}; S_{1,Q} \,|S_{3,Q}) - N\varepsilon_1.
\end{aligned}$$

In the above equations, (a) results from Fano's inequality, (b) from the fact that $H(X_1|X_2,Y_3) = 0$, (c) from the fact that given (X_1,X_2), Y_3 is independent of (S_1, S_2, S_3) and (d) from the Markov chain $(S_1^N,K_1,X_1^N) - S_3^N - (S_2^N,K_2,X_2^N)$.

With the same approaches, we have $NI(X_2;Y_3|X_1) \ge I(U_{2,Q}; S_{2,Q}|S_{3,Q}) - N\varepsilon_1$.

For the sum rate constraint, we have:

$$\begin{aligned}
&\textstyle\sum_{i=1}^N I(U_{1,i}, U_{2,i}; S_{1,i}, S_{2,i}|S_{3,i})\\
&= \textstyle\sum_{i=1}^N I(K_1, X_1^N, S_{3,i+1}^N, S_{1,1}^{i-1}, K_2, X_2^N, S_{3,1}^{i-1}, S_{2,i+1}^N; S_{1,i}, S_{2,i}|S_{3,i})\\
&= \textstyle\sum_{i=1}^N [H(S_{1,i}, S_{2,i}|S_{3,i}) -\\
&\quad H(S_{1,i}, S_{2,i}|K_1, X_1^N, S_{1,1}^{i-1}, K_2, X_2^N, S_{2,i+1}^N, S_3^N)]\\
&= \textstyle\sum_{i=1}^N [H(S_{1,i}, S_{2,i}|S_{3,i}) - H(S_{1,i}|K_1, X_1^N, S_{1,1}^{i-1}, S_3^N) -\\
&\quad H(S_{2,i}|K_2, X_2^N, S_{2,i+1}^N, S_3^N)]\\
&= H(S_1^N, S_2^N|S_3^N) - H(S_1^N|K_1, X_1^N, S_3^N) - H(S_2^N|K_2, X_2^N, S_3^N)\\
&\le H(S_1^N, S_2^N|S_3^N) - H(S_1^N|K_1, X_1^N, X_2^N, Y_3^N, S_3^N) -\\
&\quad H(S_2^N|K_2, X_1^N, X_2^N, Y_3^N, S_3^N)
\end{aligned}$$

$$\begin{aligned}
&= H(S_1^N, S_2^N | S_3^N) - H(S_1^N | K_1, X_2^N, Y_3^N, S_3^N) - \\
&\quad H(S_2^N | K_2, X_1^N, Y_3^N, S_3^N) \\
&\overset{(a)}{=} H(S_1^N, S_2^N \,|S_3^N) - H(S_1^N \,|K_1, Y_3^N, S_3^N) - H(S_2^N \,|K_2, Y_3^N, S_3^N) \\
&\le I(S_1^N, S_2^N; K_1, K_2, Y_3^N | S_3^N) \\
&= H(K_1, K_2, Y_3^N \,|S_3^N) - H(K_1, K_2, Y_3^N \,|S_3^N, S_1^N, S_2^N) \\
&\overset{(b)}{\le} H(Y_3^N \,|S_3^N) - H(Y_3^N \,|S_3^N, S_1^N, S_2^N) \; + N\varepsilon_1 \\
&\le H(Y_3^N) - H(Y_3^N \,|X_1^N, X_2^N, S_3^N, S_1^N, S_2^N) \; + N\varepsilon_1 \\
&= H(Y_3^N) - H(Y_3^N \,|X_1^N, X_2^N) \; + N\varepsilon_1 = I(X_1^N, X_2^N; Y_3^N) + N\varepsilon_1 \\
&\le N I(X_1, X_2; Y_3) + N\varepsilon_1
\end{aligned}$$

In the above equations, (a) results from the Markov chain $(S_1^N, K_1, X_1^N) - S_3^N - (S_2^N, K_2, X_2^N)$ and (b) from Fano's inequality.

REFERENCES

[1] R. Ahlswede and I. Csiszar, "Common randomness in information theory and cryptography, part I: Secret sharing," *IEEE Trans. Inf. Theory*, vol. 39, no. 4, pp. 1121–1132, Jul. 1993.

[2] U. M. Maurer, "Secret key agreement by public discussion from common information," *IEEE Trans. Inf. Theory*, vol. 39, no. 3, pp. 733–742, May 1993.

[3] I. Csiszar, P. Narayan, "Common randomness and secret key generation with a helper," *IEEE Trans. Inf. Theory*, vol. 46, no. 2, pp.344-366, Mar 2000.

[4] A. Khisti, S. Diggavi, G. Wornell, "Secret key generation using correlated sources and noisy channels," *IEEE Int.Symp. Inf. Theory*, Toronto, Canada, pp. 1005-1009, Jul. 2008.

[5] S. Salimi, M. Salmasizadeh, M. R. Aref, "Secret Key Sharing in a New Source Model: Rate Regions," *IET Communications*, Vol. 5, Issue 4, pp. 443-455, March 2011.

[6] Y. Liang and V. Poor, "Multiple access channels with confidential messages," *IEEE Trans. Inf. Theory*, vol. 54, no. 3, pp. 976-1002, Mar. 2008.

[7] M. Gastpar, "The Wyner-Ziv problem with multiple sources," *IEEE Trans. Inf. Theory*, vol. 50, no. 11, pp. 2762 - 2768, Nov. 2004.